

BE 3806

ADDITIONAL KEYBOARD

DESCRIPTION

BE 3806 is a six buttons additional keyboard that works with BM 3804 and BM 3804FM. It allows making selective calls to each system's zone. Up to eight units can be connected to the same microphone console. Each button has a fixed address to a specific system's zone.



FEATURES

- Selective zones activation
- Zones status indication
- Powered by microphone console
- Robust metal case

Rev. O Last update: 12/02/2024



TECHNICAL SPECIFICATIONS

| Console specifications | Console Type: Working with General call: Selective call: | Emergency DXT 3000 Yes Yes |
|------------------------|--|----------------------------|
| | LED indicators: | Yes |
| Connections | Daisy-chain: | Yes |
| | Max number in daisy-chain: | 8 |
| Standard compliance | Safety agency: | CE compliant |
| | EN54-16 certified: | Yes |
| | CPR number: | 0068-CPR-007/2015 |
| Size | Height: | 39 mm / 1.54 inches |
| | Width: | 78 mm / 3.07 inches |
| | Depth: | 203 mm / 7.99 inches |
| | Weight: | 0.7 kg / 1.54 lbs |
| Shipping information | Package Height: | 90 mm / 3.54 inches |
| | Package Width: | 280 mm / 11.02 inches |
| | Package Depth: | 120 mm / 4.72 inches |
| | Package Weight: | 0.9 kg / 1.98 lbs |

PART NUMBER


· 14380036

BE 3806

EAN 8024530012120



DRAWINGS









PANELS

Front panel









A&E SPECIFICATIONS

The product shall be an additional keyboard having six zone buttons that can be matched to a paging microphone / console. Up to eight additional keyboards units can be connected to the same microphone console. It shall allow making selective calls to each system's zone.