LT 7208EN

INTERFACCIA TRASFORMATORI DI LINEA

DESCRIZIONE

L'unità LT 7208EN dispone di 8 trasformatori di linea (ciascuno con potenza nominale di 80 W) per convertire le uscite altoparlanti a 8 Ohm dell'unità centrale MU 7100EN in linee a tensione costante (100 - 70 - 50 V) per diffusori aventi il trasformatore di linea. Consente svariate configurazioni di potenza, come ad esempio 8 x 80W, 4 x 160 W e 2 x 320W.

CARATTERISTICHE

- 8 trasofrmatori di linea a bordo
- Raggruppa gli amplificatori MU 7100EN
- Monitoraggio delle linee di altoparlanti
- Supporta differenti tensioni delle linee

SPECIFICHE TECNICHE

Specifiche generali	Number of inputs:	8
	Input impedance:	8 O
	Output voltage:	100 V (on request: 70 V – 50 V)
	Power output (@ 100 V)	640 W RMS
	Communication bus:	Serial
	Units connections:	FTP CAT 5, FTP CAT 6
	Power output connectors:	Euroblock
Conformità agli standard	Safety agency:	CE compliant
	Certificato EN54-16:	Yes
	Numero CPR:	1438-CPR-0241
Specifiche fisiche	Materiale Cabinet/Case:	Metal
	Montaggio a Rack:	19", 2U
Dimensioni	Altezza:	88 mm / 3.46 inches
	Larghezza:	485 mm / 19.09 inches
	Profondità:	382 mm / 15.04 inches
	Peso:	13 kg / 28.66 lbs
Informazioni di spedizione	Peso imballaggio:	14 kg / 30.86 lbs

CODICE

- **17170156**

  LT 7208EN

  EAN 8024530007126

RCF products are continually improved. All specifications are therefore subject to change without notice.

DRAWINGS



PANELS

Front panel



Rear panel



ACCESSORI

AC 7212 SPARE AM. CHANGE-OVER CARD 7802

CODICE **17170152**
EAN: 8024530007201

CJ 428CAT CABLE FTP 4x2x22 AWG CAT 5E FR (PH120)

CODICE **12399047**
EAN: 8024530016449

CJ 428E CABLE 4X2X8/10 JE-H(ST)H 300/500 V (E30/E60) (PH120)

CODICE **14380021**
EAN: 8024530012397