

# PR 63

## POWER RACK

### DESCRIPTION

The Power Rack PR-63 features the PD 63 A-419 power distribution with a 63 A Cekon power input with 5 m fixed cable. The three-phase power is distributed in a 32 A Cekon output, 4 x LKS19 output, 6 x Powercon output, 1 Powercon auxiliary output to power the CR 16-ND Control Rack. All outputs are equipped with individual RCBOs (Residual Current-operated Circuit-Breaker with Overcurrent protection) for maximum reliability. In case of damage, only the faulty output is missed while the rest of the system continues to function.



### FEATURES

- 63 Ampere Cekon power input with 5 m cable
- 32 Cekon outputs
- 4 x LKS 19 outputs
- 6 x Powercon outputs + 1 Powercon auxiliary output
- 24 x individual power line RCBOs
- 32 Ampere and Auxiliary individual front RCBOs
- Tour Grade flight case construction

**TECHNICAL SPECIFICATIONS****General specifications**

Power Input Connectors	63 Ampere Cekon with 5 m Cable
Outuputs Connector	32 Cekon, 4 x LKS 19
Powercon Outputs	6 + 1 Auxiliary
Individual Power line RCBOs	24

**Standard compliance**

CE marking:	Yes
-------------	-----

**Size**

Weight:	65.8 kg / 145.06 lbs
---------	----------------------

**Shipping informations**

Package Height:	570 mm / 22.44 inches
Package Width:	610 mm / 24.02 inches
Package Depth:	630 mm / 24.8 inches
Package Weight:	68.2 kg / 150.36 lbs

**PART NUMBER**

- **12100006**

PR 63

EAN 8024530014001